

Amendments to the Claims:

The listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

Claims 1.- 24. (Cancelled)

Claim 25. (Currently Amended) A method of controlling interference from a transmitter in one communication system to a receiver in another communication system, the method comprising:

transmitting a beacon, in a beacon transmission band, from a beacon transmitter associated with the receiver, the beacon being representative of a frequency within a beacon managed band at which the receiver is trying to receive, and the beacon transmission band being separated from the beacon managed band by using a different frequency;

listening for the beacon at a beacon receiver associated with the transmitter; and

deriving a power spectral density limit for a transmission from the transmitter, based upon the strength of the beacon received at the beacon receiver.

Claim 26. (Previously Presented) The method according to Claim 25, wherein, for a plurality of beacons received representing the same frequency, the derived transmit power spectral density limit is related to that of the beacon received at the highest power.

Claim 27. (Previously Presented) The method according to Claim 25, further comprising:

comparing the transmit power spectral density limit with a predetermined minimum transmit power spectral density required by the transmitter for that frequency; and

transmitting a signal at that frequency, only if the determined transmit power spectral density limit exceeds the minimum.

Claim 28. (Previously Presented) The method according to Claim 25, wherein a predetermined maximum transmit power spectral density is set if no beacons are received at the transmitter.

Claim 29. (Previously Presented) The method according to Claim 25, further comprising choosing a transmission frequency for the transmitter which permits the maximum power spectral density for the-transmission.

Claim 30. (Previously Presented) The method according to Claim 25,
wherein:

the transmission from the transmitter is transmitted at a frequency
derived by determining the strongest received beacon which represents any one
frequency; and

thereafter selecting, from the determined strongest beacons, the
beacon with the lowest power; and

transmitting at the frequency represented by that selected beacon.

Claim 31. (Previously Presented) The method according to Claim 29,
wherein a transmit power spectral density for a transmission from the
transmitter is set dependent upon the strength of the received beacon at the
chosen frequency.

Claim 32. (Previously Presented) The method according to Claim 25,
wherein the maximum permitted power spectral density of the transmitter is set
at the product of the receiver beacon power; and a factor by which the receiver
can be de-sensitized minus one; and the resultant of the receiver noise figure
divided by the product of the effective bandwidth at the beacon receiver for
receiving the beacon, the minimum signal to noise ratio for receiving the beacon

in its effective bandwidth and the noise figure of the beacon receiver at the transmitter.

Claim 33. (Previously Presented) The method according to Claim 25, wherein a random time division multiple access (TDMA) protocol is applied, whereby beacons representing different frequencies transmit at different times, such that over a series of cycles a beacon representing each frequency will be heard at a different time relative to another particular represented frequency, such that no one frequency at a higher power consistently blocks reception of a beacon representing another frequency at a lower power.

Claim 34. (Previously Presented) The method according to Claim 25, wherein a code division multiple access (CDMA) protocol is applied, whereby beacons representing different frequencies are distinguished from one another by different codes.

Claim 35. (Previously Presented) The method according to Claim 34, wherein a correlation period of a CDMA component of the beacon signal is controlled by a fast Fourier transform (FFT) controller.

Claim 36. (Previously Presented) The method according to Claim 25, wherein each beacon transmits a type identifier and each beacon receiver

comprises type specific correlation means, such that a beacon receiver can ignore same type beacons in determining whether or not or how much power to transmit.

Claim 37. (Previously Presented) The method according to Claim 25, wherein a receiver transmits a beacon only if interference levels exceed an acceptable value.

Claim 38. (Previously Presented) The method according to Claim 25, wherein the beacon power is adapted to the wanted signal power received at the receiver.

Claim 39. (Previously Presented) The method according to Claim 25, wherein the beacon power is adapted to the interference power received at the receiver.

Claim 40. (Previously Presented) The method according to Claim 25, wherein a bandwidth managed by a beacon is sufficiently narrow that substantial correlation of shadow fading applies across that bandwidth.

Claim 41. (Previously Presented) The method according to Claim 25, wherein each beacon occupies a frequency bandwidth which is small compared with the total bandwidth managed by that beacon.

Claim 42. (Previously Presented) The method according to Claim 41, wherein neighboring beacons in a managed bandwidth manage discrete contiguous sections of frequency, each section comprising a fraction of the beacon managed band, each beacon being separated from the frequency bandwidth which it manages by the alternate fraction.

Claim 43. (Previously Presented) The method according to Claim 42, wherein each fraction is $\frac{1}{2}$.

Claim 44. (Previously Presented) The method according to Claim 25, wherein the beacon receiver is periodically tested with an internal beacon of known power and its associated transmitter is prevented from transmitting if a beacon receiver fault occurs.

Claim 45. (Previously Presented) The method according to Claim 33, wherein beacon reception and transmission happen at the same equipment, separated in time, by arranging for reception to take place whenever transmission is not required according to schedules of the random TDMA protocol.

Claims 46. -48. (Cancelled)

Claim 49. (New) The method according to Claim 25, wherein:

the beacon transmission band is arranged as a band of frequencies
at at least one end of the beacon managed band;

there is one separate beacon signal relating to each frequency in the
beacon managed band; and

said beacon signals are multiplexed together.